

AEG



Direct On-Line (DOL) Starters



AEG Part Number	Overload Range	Horse Power Rating (Hp)						Contactor
		Single Phase		Three Phase				
		115V	230V	200V	230V	460V	575V	
I024K*SSRF026A	0.16 - 0.26A	-	-	-	-	-	-	LS4K
I024K*SSRF041A	0.25 - 0.41A	-	-	-	-	-	-	LS4K
I024K*SSRF065A	0.4 - 0.65A	-	-	-	-	-	-	LS4K
I024K*SSR010A	0.65 - 1.0A	-	-	-	-	-	1/2	LS4K
I024K*SSR015A	1.0 - 1.5A	-	1/10	-	-	1/2	3/4	LS4K
I024K*SSR019A	1.3 - 1.9A	-	1/8	-	-	3/4	1	LS4K
I024K*SSR027A	1.8 - 2.7A	-	1/6	1/2	1/2	1	2	LS4K
I024K*SSR041A	2.5 - 4.1A	1/8	1/3	3/4	3/4	2	3	LS4K
I024K*SSR063A	4.0 - 6.3A	1/4	1/2	1	1.5	3	5	LS4K
I024K*SSR085A	5.5 - 8.5A	1/3	1	2	2	5	5	LS4K
I024K*SSR120A	8.0 - 12A	1/2	1.5	3	3	5	7.5	LS4K
I027K*SSR120A	8.0 - 12A	1/2	2	3	3	7.5	10	LS7K
I027K*SSR160A	10 - 16A	1	2	3	5	10	10	LS7K
I027K*SSR180A	14.5 - 18A	1	3	5	5	10	15	LS7K
I0211K*SSR220A	17.5 - 22A	1.5	3	5	7.5	15	15	LS11K
I0212K*SSR260A	21 - 26A	2	3	7.5	7.5	15	20	LS12K
I0215K*SSR320A	25 - 32A	2	5	10	10	20	25	LS15K
I0218K*SSR400A	30 - 40A	3	5	10	10	25	25	LS18K

** For Single Phase Starters ADD "S" at the beginning of the Part Number **

Contactor Coil Suffix are designated above and left

* - Ordering Code Example: **SI024KASSR063A**

Note: The AEG (LSK Series) contactors are IEC and NEMA rated.

Please contact our factory for further information concerning these dual ratings.



Coil Voltages - AC Coils (*)		
Suffix	50hz	60Hz
G	24V	24V
A	110V	115V
C	220V	230V
H	230V	277V
E	380V	480V
F	500V	600V