



3-Pole Contactors (10hp @ 575V)
ECX18



Contactor Selection and Data



| | | HP @ 575V | | | |
|--|----------------------------|----------------|-----|---|---|
| | | 10hp | | | |
| AC Contactors | Full Voltage Non-Reversing | ECX18-* | - | - | - |
| | Reversing | RECX18-* | - | - | - |
| Auxiliary Contacts | Maximum Aux Contacts | 5 (1 Built In) | - | - | - |
| | Maximum Contact Blocks | 1 | - | - | - |
| Auxiliary Contacts Amperage (A600, P600) | | 10A | - | - | - |
| AC-1 (Resistive) Amperage | | 32A | - | - | - |
| Full Load Amperage @ 240V (AC-3) | | 22A | - | - | - |
| Horsepower Ratings | Single Phase | 115V | 1 | - | - |
| | | 230V | 3 | - | - |
| | Three Phase | 200V | 7.5 | - | - |
| | | 230V | 7.5 | - | - |
| | | 460V | 10 | - | - |
| | 575V | 10 | - | - | |

| * - Coil Selection | | | Coil Data | | |
|--------------------|----|---------------|-------------------------|--------------|---|
| AC | DC | Suffix | - | AC | - |
| 24V | - | G | Inrush Burdon | 70VA | - |
| 120V | - | A | Holding Burdon | 8VA | - |
| 208/230V | - | C | Pick Up Voltage (+/-) | 10+ / -15 % | - |
| 480V | - | E | Drop Out Voltage (-) | (-) 20-75% | - |
| 600V | - | F | Maximum Operations | | |
| | | | Mechanical Operations | 6,000,000 | - |
| | | | Electrical Operations | 600,000 | - |
| Dimensions | | Height (Inch) | Width (Inch) | Depth (Inch) | |
| | | 3.0" | 1.85" | 3.43" | |